



## CPL2

Clapeta de dozaj motorizata tot sau nimic



TIP

Circular  
Tot sau nimic



APLICARE

Dozaj



DIMENSIUNI

100 la 315 mm



COMANDA

Motorizat



ACCES PRODUS ON LINE

### AVANTAJE

- Usor de instalat.
- Deschiderea clapetei motorizata.
- Inchiderea clapetei : necesita un contact on/off (separat).

### APLICARE / UTILIZARE

- Isolarea unei conducte de celelate.
- Utilizare pentru ventilatie, aer conditionat.

### CONSTRUCTIE / COMPOZITIE

- Carcasa si lama in otel galvanizat cu garnitura.
- Motor electric si borna protejate de un capac.
- Pentru toate diametrele, lungime = 200 mm.
- Temperatura limita de folosire = 60 °C.
- Timp de raspuns la inchidere si la deschidere = 5 s.
- Presiunea de functionare ≤ 200 Pa.

### RACORDARE ELECTRICA

- Conexie pe borna (3 fire) prin cablu 1 x 0,75 mm
- Tensiune de alimentare : mono 230 Volt.



CTP

CTR

## CTP / CTR

Clapete de dozaj motorizate cu doua debite (CTP), tot sau nimic (CTR)



TIP

Circular / doua debite  
Tot sau nimic



APLICARE

Dozaj  
Isolare



DIMENSIUNI

125 la 200 mm



COMANDA

Motorizat



ACCES PRODUS ON LINE

### AVANTAJE

- Usor de instalat.

### APLICARE / UTILIZARE

- Utilizare pentru ventilatie, aer conditionat.
- CTR : Isolarea unei conducte de celelate.
- CTP : gestiunarea doua debite (nominal /maximal).

### CONSTRUCTIE / COMPOZITIE

- Carcasa si lama in plastic, virole din otel galvanizat.
- Motor electric si borna protejate de un capac.
- Temperatura limita de folosire = 60 °C.
- Tmp de raspuns la inchidere si la deschidere = 8 s.
- PrPresiunea de functionare ≤ 200 Pa.
- CTR : deschis cand este alimentat.
- CTP : regulator de debit maxi et mini. Mare debit cand este alimentat.

Debite disponible		
Registru CTP doua débite	Debit mini (nealimentat)	Debit maxi (alimentat)
Ø 125	15 à 50 m <sup>3</sup> /h	50 à 180 m <sup>3</sup> /h
Ø 160	15 à 100 m <sup>3</sup> /h	120 à 300 m <sup>3</sup> /h
Ø 200	15 à 100 m <sup>3</sup> /h	120 à 500 m <sup>3</sup> /h

### RACORDARE ELECTRICA

- Pentru siguranta , a se prevedea un disjonctor faza + neutru 1 A.
- A se racorda cablu pe cutie de racordare (borna 2 fire).
- Tensiune de alimentare : mono 230 Volt. (24V optional)